



Solder J22 to connect I Out 1 and I Out 2.

Solder J23 to connect I Out 3 and I Out 4.

Place a jumper between J2 pin 10 and GND for differential output (4 Outputs X 1.2mA).
 With J2 pin 10 floating and J22 and J23 on DAC board soldered, output is single-ended
 with analog interpolation (2 X 2.4mA).

Use buttons + and - to adjust the volume level.
 Press Menu button to enter the input select state. In this state the current input LED is blinking.
 If no button is pressed for 3 seconds, the volume adjustment state is resumed.

Audiobyte OEM	
RD-30 Rev.B Connection Diagram	5/28/2012